Attenuator 5 to 2500 MHz

Technical Data

UTF-025

Features

- 35 dB Attenuation Range
- < 1.5:1 VSWR


Applications

- Open and Closed Loop Gain Control
- AGC Circuits


Description

The UTF-025 is a thin-film voltage-controlled RF attenuator that operates from 5 to 2500 MHz. Utilizing PIN diodes, attenuation over frequency typically has ± 0.4 to ± 0.6 dB flatness over the complete control voltage range. On the average, the attenuation will change roughly 5 dB per 2-volt increment. The UTF-025 is available in either the TO-8 hermetic case or connectorized TC-1 package.


Pin Configuration TO-8F



TC-1



Schematic



Maximum Ratings


Parameter	Maximum
DC Voltage	+18 Volts
Continuous RF Input Power	+23.0 dBm
Operating Case Temperature	−55 to +125°C
Storage Temperature	−62 to +150°C
"R" Series Burn-In Temperature	+125°C


Weight: (typical) 2.1 grams


Electrical Specifications (Measured in 50 Ω system @ +15 VDC nominal)

Symbol	Characteristic	$Typical T_{\rm C} = 25^{\circ}C$	Guaranteed Specifications		Unit
			$T_{\rm C} = 0 \text{ to } 50^{\circ}\text{C}$	$T_{\rm C}$ = -55 to +85°C	Unit
BW	Frequency Range	5-2500	5-2000	5-2000	MHz
_	Attenuation, Min. $(V_C = 0 V)$				
	5-500 MHz	33.0	_	_	dB
	500-1000 MHz	28.0	_	_	dB
	1000-2000 MHz	23.0	_	_	dB
	2000-2500 MHz	17.0	_	_	dB
_	Insertion Loss, Max. $(V_C = +15 V)$				
	5-1000 MHz	2.0	_	_	dB
	1000-2000 MHz	2.8	_	_	dB
	2000-2500 MHz	3.5		_	dB
_	VSWR (Worst Case In Attenuation				
	Range)				
	5-1000 MHz	1.5:1		_	_
	1000-2000 MHz	1.8:1	_	_	_
_	Intercept Point	+30		_	dBm
_	Flatness Over Frequency (Min. to 15 dB)				
	5-1000 MHz	±0.4		_	dB
	1000-2000 MHz	±0.6		_	dB
	(Min. to 20 dB)				
	5-1000 MHz	±0.8	_	_	dB
—	Switching Speed (10% to 90%)	75	_	_	μs
	(ON to OFF or OFF to ON)				
_	Bias Voltage	+15	_	_	VDC
_	Bias Current	15	—	_	mA
	Control Voltage	1 to +15	_	_	VDC
	Control Current	0 to 7	_	_	mA


Typical Performance At 25°C Temperature (at +15 VDC unless otherwise noted)











Due to $\rm R_S$ vs. $\rm I_F$ differences in pin diodes used in this product, internal drive compensation is done to optimize VSWR. This correction can affect the Attenuation vs. Control Voltage from unit to unit to the extent shown in the graph.

















Product Options





Note: No R-Series screening is available in the TC-1 case as the case is non-hermetic.

Case Drawings TC-1



TYPICAL WEIGHT WITH CONNECTORS = 21.5 GRAMS

NOTES: 1. THE TC-1 CASE IS A NON-HERMETIC CASE.
2. THE ONLY CONNECTOR OPTION AVAILABLE FOR THE TC-1 CASE IS THE -1, SMA FEMALE CONNECTORS AT BOTH INPUT AND OUTPUT PORTS.


NOTES (UNLESS OTHERWISE SPECIFIED):


1. DIMENSIONS ARE SPECIFIED IN INCHÉS


2. TOLERANCES: $xx \pm .02$

 $xxx \pm .010$

Case Drawings TO-8F







APPROXIMATE WEIGHT 2.1 GRAMS

NOTES (UNLESS OTHERWISE SPECIFIED):
1. DIMENSIONS ARE SPECIFIED IN INCHES

2. TOLERANCES: $xx \pm .02$

 $xxx \pm .010$

Contact Teledyne Microwave Solutions: 650-691-9800 650-962-6845 fax

Check for updates: www.teledynemicrowave.com